

# RFID Tag Reader

Typing or barcode-scanning a 24-character RFID tag number into software for every piece of product is a time consuming reality of the manual tag association process, but it doesn't have to be. With the RFID Tag Reader, it can become a thing of the past. Simply connect this read point to your computer via USB, place the RFID tag within the read field and the tag information is transferred to your computer – saving time, eliminating human error, and optimizing your workflow.



# FEATURES

## AT A GLANCE

Model number	US   EUR TS089
External dimension H x W x D	US 0.9 in. x 2.4 in. x 5.2 in. EUR 20 mm. x 61 mm. x 133 mm.
Operating temperature range	0 °C to +50.0 °C
Storage temperature range	-40.0 °C to +70.0 °C
Interfaces	USB HID keyboard emulation
Power consumption	Maximum: 3.5 W, USB powered Idle: 1.0 W, USB powered
RAIN RFID frequency	US 902 to 928 MHz EUR 865 to 868 MHz
RFID read range	Adjustable from 1 ft. to 6 ft.
Certifications	RAIN, UL, cUL, ECHA, FCC, CE, RoHS, REACH, IP41 Rated, NOM, NYCE



## BENEFITS

Read distance: configurable up to 2 meters (6 ft) dependent on power level and tag size

Certified for use globally

LEDs indicate successful tag read

Audible confirmation

RFID Tag Reader  
in action

### WHAT IS IT GOOD FOR?

#### APPLICATIONS

Point of use  
Consumption events  
RFID tag association  
RFID tag presence / absence

#### LOCATION USE

Hospitals  
Labs  
Dental offices  
Operating rooms  
Stockrooms  
Supply rooms  
Medical device manufacturers and distributors  
Consignment inventory